



NEW YORK UNIVERSITY

Institute of Mathematical Sciences

Division of Electromagnetic Research

RESEARCH REPORT No. BR-28

The Discriminant of Hill's Equation

WILHELM MAGNUS

Mathematics Division

Air Force Office of Scientific Research

Contract No. AF 49(638)229

Project No. 47500

MAY, 1959

NEW YORK UNIVERSITY
Institute of Mathematical Sciences
Division of Electromagnetic Research

Research Report No. RR-28

THE DISCRIMINANT OF HILL'S EQUATION

Wilhelm Magnus

Wilhelm Magnus.
Wilhelm Magnus

Sidney Borowitz
Sidney Borowitz
Acting Director

May, 1959

Qualified requestors may obtain copies of this report from the ASTIA Document Service Center, Arlington Hall Station, Arlington 12, Virginia. Department of Defense contractors must be established for ASTIA services, or have their 'need-to-know' certified by the cognizant military agency of their project or contract.

Abstract

Explicit expressions for the discriminant of Hill's equation up to terms of order four are being calculated. It is shown that these formulas permit a new proof of a theorem about the asymptotic distribution of the characteristic values. They also permit the derivation of certain summation formulas involving the lengths of the intervals of instability and the Fourier Coefficients of the periodic function appearing in Hill's equation.

Table of Contents

	<u>Page</u>
1. Introduction	1
2. Notations and elementary results	2
3. Borg's Theorem	5
4. Formulas for the discriminant	6
5. Proof of Borg's Theorem	10
6. Some relations between the characteristic values	18
7. Appendix: Methods for the computation of Δ	27
References	40

1. Introduction

The discriminant of Hill's equation is an analytic function $\Delta(\lambda)$ of the characteristic parameter λ appearing in the equation. The zeros of $\Delta - 2$ and of $\Delta + 2$ determine the values λ for which the equation has periodic solutions; the intervals between the zeros of $\Delta^2 - 4$ determine the region of stability and of instability for the solutions of the equation. Therefore, it is of importance for all practical (i.e. numerical) purposes to find expressions for $\Delta(\lambda)$ which may be useful for a computation of the zeros of $\Delta^2 - 4$. Although it is known, in principle, how to find a suitable expansion for $\Delta(\lambda)$, it turns out that the actual computation of the first terms of such an expansion is not an easy task. In Section 4 of this report, the first four terms of the expansion in question are given explicitly. In the Appendix, the various methods for calculating these terms explicitly are discussed and the steps of the computation are indicated.

Apart from being useful for numerical purposes, a discussion of $\Delta(\lambda)$ may also serve for the derivation of general theorems. In Section 4, we shall show how a theorem due to G. Borg^[1] can be derived from our expression for Δ , and in Section 6 we shall supplement Borg's result by relations for the zeros of $\Delta - 2$ and of $\Delta + 2$. In the special case where Hill's equation has an even function as its coefficient, we shall be able to prove additional results of the same type, involving the sum of the lengths of the intervals of instability. There, results are connected with a theorem derived by A. Erdélyi^[2] who gave an approximate formula for the length of the intervals of instability in the case where the coefficient of Hill's equation is 'almost' constant. We wish

to mention here that Erdélyi's paper^[2] also contains some applications of the theory of Hill's equation to the investigation of electric circuits and a large number of references to other applications.

Section 2 contains notations and some elementary results. For a proof of these results we refer to reference ^[3], where the same notations are being used as in the present report.

The method used in Section 6 for proving relations between the characteristic values is due to Schaefer^[4].

2. Notations and elementary results

We shall write Hill's equation in the form

$$(2.1) \quad y'' + [\lambda + g(x)]y = 0 ,$$

where λ is a parameter and

$$(2.2) \quad g(x) = \sum_{n=-\infty}^{\infty} g_n e^{2inx}$$

is a real valued periodic function of x with period π ; we have

$$(2.3) \quad g_n = \overline{g_{-n}} \quad (n = 0, \pm 1, \pm 2, \dots)$$

where a bar denotes the conjugate complex of a quantity, and, unless otherwise stated, we shall assume that, for a certain constant $N > 0$,

$$(2.4) \quad |n^2 g_n| \leq N .$$

Condition (2.4) is satisfied whenever $g(x)$ has a second derivative; it could be weakened without affecting the results. As a normalization, we shall always introduce the condition

$$(2.5) \quad g_0 = 0$$

which is equivalent to

$$\int_0^{\pi} g(x) dx = 0.$$

By $y_1(x)$ and $y_2(x)$ we denote the solutions of (2.1) which satisfy the initial conditions

$$(2.6) \quad y_1(0) = 1, y_1'(0) = 0, y_2(0) = 0, y_2'(0) = 1.$$

The discriminant $\Delta(\lambda)$ of Hill's equation can be defined by

$$(2.7) \quad \Delta = y_1(\pi) + y_2'(\pi).$$

The transcendental equations in λ :

$$(2.8) \quad \Delta(\lambda) - 2 = 0$$

and

$$(2.9) \quad \Delta(\lambda) + 2 = 0$$

have an infinitude of real roots (and no others) which can be arranged in a sequence

$$(2.10) \quad \lambda_0 < \lambda_1' \leq \lambda_2' < \lambda_1 \leq \lambda_2 < \lambda_3' \leq \lambda_4' < \lambda_3 \leq \lambda_4 \dots$$

where $\lambda_0, \lambda_1, \lambda_2, \dots$ are the roots of (2.8) and $\lambda'_1, \lambda'_2, \lambda'_3, \dots$ are the roots of (2.9). If λ equals a root of (2.8), then (2.1) has a non trivial solution (i.e. a solution other than $y \equiv 0$) which is periodic and of period π ; if λ satisfies (2.9), then (2.1) has a non trivial solution of period 2π , and there do not exist any other cases where (2.1) has a non trivial solution of period π or 2π .

The intervals $(-\infty, \lambda_0)$, (λ'_1, λ'_2) , (λ_1, λ_2) , (λ'_3, λ'_4) , (λ_3, λ_4) , ... are called intervals of instability. Wherever λ is contained in such an interval, there exists at least one unbounded solution of (2.1). The intervals of instability include their boundary points provided that they contain at least two different points; if $\lambda'_1 = \lambda'_2$, the corresponding interval of instability disappears. We shall label the intervals of instability by calling $(-\infty, \lambda_0)$ the zero-th interval, (λ'_1, λ'_2) the first interval and so on, and, accordingly, we shall talk about even and odd intervals of instability.

The open set of the λ -axis which remains after the intervals of instability have been taken out is a collection of open intervals, the intervals of stability. If λ belongs to such an interval, all solutions of (2.1) are bounded in $(-\infty, \infty)$.

The numbers $\lambda_0, \lambda'_1, \lambda'_2, \dots$ are called characteristic values of λ . Whenever two of these coincide, an interval of instability disappears; for the corresponding value of $\lambda = \lambda'_{2n-1} = \lambda'_{2n}$ or $\lambda = \lambda_{2n-1} = \lambda_{2n}$, where $n = 1, 2, 3, \dots$, all solutions of (2.1) are periodic with period 2π or π respectively. We shall have $\lambda'_{2n-1} = \lambda'_{2n}$ or $\lambda_{2n-1} = \lambda_{2n}$ if, and only if, (2.7) or (2.8) respectively has a double root; no root of these equations can have a multiplicity greater than 2. For a proof of these facts see [3].

3. Borg's Theorem

The following result is due to G. Borg^[1]:

Theorem 1. For large values of $n = 1, 2, 3, \dots$ the asymptotic distribution of the characteristic values of Hill's equation is given by

$$\lambda'_{2n-1} = (2n-1)^2 + \frac{C}{(4n-2)^2} + o(n^{-2})$$

$$\lambda'_{2n} = (2n-1)^2 + \frac{C}{(4n-2)^2} + o(n^{-2})$$

$$\lambda_{2n-1} = 4n^2 + \frac{C}{(4n)^2} + o(n^{-2})$$

$$\lambda_{2n} = 4n^2 + \frac{C}{(4n)^2} + o(n^{-2})$$

where

$$C = \frac{1}{\pi} \int_0^{\pi} |g(x)|^2 dx = 2 \sum_{n=1}^{\infty} g_n g_{-n} .$$

We shall prove Theorem 1 fully for the special case where all but a finite number of the g_n are zero. In this case, we may replace $o(n^{-2})$ by $\mathcal{O}(n^{-5/2})$ which shows that the intervals of instability are of the order of magnitude $n^{-5/2}$ as $n \rightarrow \infty$. In the general case, we shall indicate how our proof has to be modified in order to obtain Borg's Theorem.

4. Formulas for the discriminant

We shall derive Borg's Theorems from the following two lemmas and from Theorem 3 formulated below:

Lemma 1 The discriminant $\Delta(\lambda)$ is an entire function of λ which admits an expansion

$$\Delta(\lambda) = \sum_{n=0}^{\infty} \Delta_n(\lambda)$$

in which $\Delta_n(\lambda)$ is a homogeneous form in the g_r ($r = \pm 1, \pm 2, \dots$) such that the coefficient of

$$g_{r_1} g_{r_2} \cdots g_{r_n}$$

is an entire function of λ of the type

$$R_n(\lambda) \frac{\sin \pi \sqrt{\lambda}}{\sqrt{\lambda}} + S_n(\lambda) \cos \pi \sqrt{\lambda} .$$

There $R_n(\lambda)$, $S_n(\lambda)$ are rational functions of λ the poles of which are located at some of the points

$$\sqrt{\lambda} = \ell_1 + \ell_2 + \dots + \ell_k$$

where $k \leq n$ and where ℓ_1, \dots, ℓ_k are certain numbers of the set consisting of r_1, r_2, \dots, r_n . For large positive values of λ ,

$$\left| \Delta(\lambda) - \sum_{n=0}^N \Delta_n(\lambda) \right| = \mathcal{O}(\lambda^{-(N+1)/2}) .$$

Lemma 1 is an immediate consequence of results proved elsewhere; it follows from Theorem 2.5 and from the proof of Theorem 2.4 in [3]. The other lemma needed for the proof of Borg's Theorem will be derived in the Appendix (Section 7). We may formulate it as follows.

Lemma 2. Let $R_n(\lambda)$ and $S_n(\lambda)$ be defined as in Lemma 1. Then the excess of the degree of the denominator over the degree of the numerator is, for $R_n(\lambda)$, at least

$$n - \frac{1}{2} \left[\frac{n}{2} \right] - \frac{1}{2}$$

and for $S_n(\lambda)$ at least

$$n - \frac{1}{2} \left[\frac{n}{2} \right]$$

where $[(n/2)]$ is the largest integer not exceeding $n/2$.

The last result which we shall need for the proof of Borg's Theorem is an explicit expression for Δ_0 , Δ_1 , Δ_2 , Δ_3 and Δ_4 . A derivation for these expressions will be given in the Appendix (Section 7). The formulas needed may be written in the following manner:

Theorem 2. For $n \leq \lambda$, $\Delta_n(\lambda)$ is given by the formulas:

$$\Delta_0(\lambda) = 2\cos\pi\sqrt{\lambda}.$$

$$\Delta_1(\lambda) = 0$$

$$\Delta_2(\lambda) = \frac{\pi \sin \pi \sqrt{\lambda}}{2 \sqrt{\lambda}} \sum_{r=1}^{\infty} \frac{g_r g_{-r}}{\lambda - r^2}$$

$$\Delta_3(\lambda) = - \frac{\pi \sin \pi \sqrt{\lambda}}{8 \sqrt{\lambda}} \sum_{r,s=1}^{\infty} \frac{(g_r g_s g_{-r-s} + g_{-r} g_{-s} g_{r+s})(3\lambda - r^2 - s^2 - rs)}{(\lambda - r^2)(\lambda - s^2) [\lambda - (r+s)^2]}$$

$$\Delta_4(\lambda) = - \pi^2 \frac{\cos \pi \sqrt{\lambda}}{16 \lambda} \left\{ \sum_{r=1}^{\infty} \frac{g_r g_{-r}}{\lambda - r^2} \right\}^2 - \frac{\pi \sin \pi \sqrt{\lambda}}{64 \sqrt{\lambda}} \sum_{r=1}^{\infty} (g_r g_{-r})^2$$

$$\times \frac{30\lambda^2 - 70\lambda r^2 - 16r^4}{(\lambda - r^2)^3 (\lambda - 4r^2)} - \frac{\pi \sin \pi \sqrt{\lambda}}{8 \sqrt{\lambda}} \sum_{\substack{r,s=1 \\ r > s}}^{\infty} (g_r g_{-r} g_s g_{-s}) \left\{ \frac{5\lambda^2 - 3\lambda(r^2 + s^2) + r^2 s^2}{\lambda(\lambda - r^2)^2 (\lambda - s^2)^2} \right.$$

$$\left. + \frac{10\lambda - 2r^2 - 2s^2}{(\lambda - s^2)(\lambda - r^2) [\lambda - (r-s)^2] [\lambda - (r+s)^2]} \right\} + \sum_{k, \ell, m=1}^{\infty} (G_{k, \ell, m} + G_{-k, -\ell, -m})$$

$$\times S_{k, m, \ell}(\lambda) + \sum_{\substack{k \neq \ell \\ k, \ell=1}}^{\infty} \sum_{m=1}^{\infty} (g_{\ell+m} g_k g_{-\ell} g_{-k-m} + g_{-\ell-m} g_{-k} g_{\ell} g_{k+m}) S_{k, m, \ell}(\lambda)$$

where

$$G_{k,\ell,m} = g_k g_\ell g_m g_{-k-\ell-m} + g_{k+\ell+m} g_m g_{-k-m} g_{-\ell-m}$$

and $S_{k,m,\ell}^{(\lambda)}$ is defined by

$$4S_{k,\ell,m}^{(\lambda)} = \frac{1}{km} \sigma(k+m, \ell) - \frac{1}{k(k+m)} \sigma(m, \ell) - \frac{1}{m(k+m)} \sigma(k, \ell+m),$$

where

$$\sigma(\ell, m) = \frac{\pi \sin \pi \sqrt{\lambda}}{8 \sqrt{\lambda}} \frac{(\lambda - \ell^2 - m^2 - \ell m)}{(\lambda - \ell^2)(\lambda - m^2) [\lambda - (\ell+m)^2]}.$$

We have embedded in Theorem 3 more information about Δ than would be necessary to prove Borg's Theorems. This has been done since the full explicit expression of Δ_3 and Δ_4 may be expected to be useful for numerical calculations in specific applications.

In the case where $g_{-n} = -g_n$, i.e. where $g(-x) = -g(x)$, we have the

Corollary of Theorem 3: If $g(x)$ is an odd function of x ,

$\Delta_n \equiv 0$ whenever n is an odd integer.

This result is a trivial by-product of the expression for Δ as an infinite determinant which will be used in the Appendix.

5. Proof of Borg's Theorem

In order to derive Theorem 1 from Lemmas 1 and 2 and from Theorem 2, we shall make the following assumption:

Only a finite number of the Fourier coefficients g_n of $g(x)$ is different from zero.

This assumption will simplify the proof and will help to clarify the method. We shall indicate afterwards what has to be done if we wish to replace this assumption by a weaker one such as the inequality (2.4). If only finitely many of the g_n are different from zero, it is obvious that, for $\lambda \rightarrow \infty$, $\lambda > 0$,

$$(5.1) \quad \sum_{r=1}^{\infty} \frac{g_r g_{-r}}{\lambda - r^2} = \lambda^{-1} \sum_{r=1}^{\infty} g_r g_{-r} + \mathcal{O}(\lambda^{-2})$$

$$(5.2) \quad \sum_{\substack{r,s=1 \\ r > s}}^{\infty} g_r g_{-r} g_s g_{-s} \frac{5\lambda^2 - 3\lambda(r^2 + s^2) + r^2 s^2}{\lambda(\lambda - r^2)^2 (\lambda - s^2)^2} = \mathcal{O}(\lambda^{-3})$$

$$(5.3) \quad \sum_{r,s=1}^{\infty} g_r g_{-r} g_s g_{-s} \frac{10\lambda - 2r^2 - 2s^2}{(\lambda - r^2)(\lambda - s^2) [\lambda - (r-s)^2] [\lambda - (r+s)^2]} = \mathcal{O}(\lambda^{-3})$$

$$(5.4) \quad \sum_{r=1}^{\infty} (g_r g_{-r})^2 \frac{30\lambda^2 - 70\lambda r^2 - 16r^4}{(\lambda - r^2)^3 (\lambda - 4r^2)} = \mathcal{O}(\lambda^{-2})$$

$$(5.5) \quad \frac{\sigma(\mathcal{L}, m)}{\sin \pi \sqrt{\lambda}} = \mathcal{O}(\lambda^{-5/2})$$

$$(5.6) \quad \frac{S_{k, \mathcal{L}, m}(\lambda)}{\sin \pi \sqrt{\lambda}} = \mathcal{O}(\lambda^{-7/2})$$

Also, it follows from Lemma 2 that

$$(5.7) \quad \Delta_5(\lambda) = (\sin \pi \sqrt{\lambda}) \mathcal{O}(\lambda^{-7/2}) + (\cos \pi \sqrt{\lambda}) \mathcal{O}(\lambda^{-4})$$

$$(5.8) \quad \Delta_6(\lambda) = (\sin \pi \sqrt{\lambda}) \mathcal{O}(\lambda^{-9/2}) + (\cos \pi \sqrt{\lambda}) \mathcal{O}(\lambda^{-4})$$

and therefore Lemma 1 shows that, for $\lambda \rightarrow \infty$,

$$(5.9) \quad \left| \Delta - \sum_{n=0}^6 \Delta_n \right| = \mathcal{O}(\lambda^{-7/2}).$$

Consider now the equation

$$(5.10) \quad 2 - \Delta = 4 \sin^2 \frac{\pi}{2} \sqrt{\lambda} - \Delta_2 - \Delta_3 - \Delta_4 - \dots = 0.$$

If λ is large, all terms except $\sin^2 \frac{\pi}{2} \sqrt{\lambda}$ will be of the order of magnitude of $\lambda^{-3/2}$ or smaller, and therefore we will have

$$\sin \frac{\pi}{2} \sqrt{\lambda^*} = \mathcal{O}(\lambda^{*-3/4})$$

if λ^* is a large root of $2 - \Delta = 0$. Therefore,

$$(5.11) \quad \lambda^* = (2n + \epsilon)^2 ,$$

where n is an integer and where

$$(5.12) \quad \epsilon = \mathcal{O}(\lambda^{*-3/4}) = \mathcal{O}(n^{-3/2}).$$

Since we are interested in λ^* and not in $\sqrt{\lambda^*}$, we may assume that $n > 0$.

In terms of ϵ ,

$$\begin{aligned} 4\sin^2 \frac{\pi}{2} \sqrt{\lambda^*} &= \pi^2 \epsilon^2 + \mathcal{O}(\epsilon^4) = \pi^2 \epsilon^2 + \mathcal{O}(n^{-6}) \\ \sin \pi \sqrt{\lambda^*} &= \pi \epsilon + \mathcal{O}(\epsilon^3) = \pi \epsilon + \mathcal{O}(n^{-9/2}) . \end{aligned}$$

Therefore, we find from (2.10), by substituting the explicit expressions for Δ_2 , Δ_3 , Δ_4 from Theorem 3 and by using the inequalities (5.1) to (5.9):

$$(5.13) \quad \pi^2 \left[\epsilon - \frac{1}{32n^3} \sum_{r=1}^{\infty} g_r g_{-r} \right]^2 = \epsilon \mathcal{O}(n^{-5}) + \mathcal{O}(n^{-8}).$$

From (2.12) we find now

$$\pi^2 \left[-\frac{1}{32n^3} \sum_{r=1}^{\infty} g_r g_{-r} \right]^2 = \mathcal{O}(n^{-13/2})$$

and therefore $\epsilon = \mathcal{O}(n^{-3})$. But this implies that, in (2.13)

$$(5.14) \quad \pi^2 \left[\epsilon - \frac{1}{32n^3} \sum_{r=1}^{\infty} g_r g_{-r} \right]^2 = \mathcal{O}(n^{-8})$$

and therefore we have the result

$$(5.15) \quad \epsilon = \frac{1}{32n^3} \sum_{r=1}^{\infty} g_r g_{-r} + \mathcal{O}(n^{-4})$$

which leads immediately to

$$(5.16) \quad \lambda^* = (2n + \epsilon)^2 = 4n^2 + \frac{2}{4n^2} \sum_{r=1}^{\infty} g_r g_{-r} + \mathcal{O}(n^{-3})$$

which agrees with the result stated in Theorem 1. Actually, our remainder term is somewhat smaller than the one mentioned there, but this is due to the fact that (2.1) has to be replaced by a weaker inequality if there are infinitely many $g_r \neq 0$.

Observe that in (5.15) the coefficient of the leading term n^{-3} cannot vanish unless all of the g_r vanish, in which case everything is trivial. Therefore, n^{-3} is the true leading term in the asymptotic expansion for ϵ except for the trivial case $\epsilon \equiv 0$.

Equation (5.16) is not yet the equivalent to the full statement of Theorem 1. What is missing is the proof that (2.14) actually has two roots close to $\sqrt{\lambda} = 2n$ (that these must be real is an elementary result, see [3]), and that these roots are the n -th and the $(n+1)$ -st roots of $2 - \Delta(\lambda) = 0$. To show this, we consider the function

$$D(\lambda, \delta) ,$$

$$0 < \delta < 1$$

which is defined as the discriminant of the equation

$$y'' + [\lambda + \delta g(x)]y = 0 .$$

Clearly, we have

$$D(\lambda, 1) = \Delta(\lambda) , \quad D(\lambda, 0) = 2\cos\pi\sqrt{\lambda} .$$

We know that the equation

$$D(\lambda, \delta) - 2 = 0 \quad (0 \leq \delta \leq 1)$$

has real zeros only, and we can show by the method used in proving Lemma 1 that for $\lambda \rightarrow \infty$

$$(5.17) \quad |D(\lambda, \delta) - D(\lambda, 0)| \leq \frac{M}{\lambda} \quad (M = \text{constant})$$

uniformly in δ . Also, we can show that there exists a negative constant

$-\Lambda$ such that

$$(5.18) \quad |D(-\Lambda, \delta)| > M' \quad (M' = \text{constant})$$

independent of δ for $0 \leq \delta \leq 1$. Now let $\lambda = \alpha + i\beta$ be a complex variable where α, β are real and consider the boundary R of the rectangle defined by

$$-\Lambda \leq \alpha \leq (2n + \frac{1}{2})^2, \quad -1 \leq \beta \leq 1 .$$

We know from (2.17) and (2.18) that $\Delta(\lambda, \delta) - 2 \neq 0$ on R for $0 \leq \delta \leq 1$.

We also know that the zeros of the equation

$$\Delta(\lambda, \delta) - 2 = 0$$

which are located within R are continuous functions of δ . Let $N(\delta)$ be their number. Then

$$(5.19) \quad N(\delta) = \frac{1}{2\pi i} \int_R \frac{\Delta'}{\Delta - 2} d\lambda$$

where $\Delta' = \partial\Delta/\partial\lambda$. Now the integral on the right-hand side is a continuous function of Δ since the denominator never vanishes on the path of integration, and therefore the left-hand side is a constant since it is an integer. For $\delta = 0$, we find

$$N(0) = N(\delta) = 2n + 1,$$

and therefore there are exactly $2n + 1$ zeros of $\Delta(\lambda) - 2$ in the interval $-N \leq \lambda \leq (2n + \frac{1}{2})^2$. Similarly, there are exactly $2n - 1$ zeros of $\Delta(\lambda) - 2$ in $-N \leq \lambda \leq (2n - \frac{3}{2})^2$, and therefore there are exactly two zeros in $2n - 3/2 \leq \lambda \leq 2n + 1/2$ which must be the two roots of (5.14) close to $\sqrt{\lambda} = 2n$ and they must satisfy the relation (2.16) for λ^* . This proves Theorem 1 in the case where only finitely many of the g_n are different from zero. In order to indicate what has to be done in general, we shall proceed as follows:

Assume that

$$(5.20) \quad \sum_{n=1}^{\infty} g_n g_{-n} n^2 < \infty,$$

i.e. that $g(x)$ has a square integrable first derivative. We wish to estimate the absolute value of

$$\begin{aligned} D(\lambda) &= \sum_{n=1}^{\infty} \left(\frac{g_n g_{-n}}{\lambda - n^2} - \frac{g_n g_{-n}}{\lambda} \right) \sin \pi \sqrt{\lambda} \\ &= \sum_{n=1}^{\infty} \frac{n^2 g_n g_{-n}}{\lambda(\lambda - n^2)} \sin \pi \sqrt{\lambda} \end{aligned}$$

for $\lambda \rightarrow \infty$. In the case of a finite sum, we would have $|D(\lambda)| = \mathcal{O}(\lambda^{-2})$.

Now all we can do is to prove

$$(5.21) \quad |D(\lambda)| = \mathcal{O}(\lambda^{-3/2}) \quad (\lambda \rightarrow \infty).$$

To do this, let $\lambda = \omega^2$ and observe that

$$i \int_{-\pi}^{\pi} e^{i\omega x} \sum_n g_n g_{-n} \sin nx \, dx = -2(-1)^n \frac{n^2 \sin \omega \pi}{\omega^2 - n^2} g_n g_{-n}$$

and therefore

$$\begin{aligned}\lambda D(\lambda) &= -\frac{i}{2} \int_{-\pi}^{\pi} \left(\sum_{n=1}^{\infty} (-1)^n n g_n g_{-n} \sin nx \right) e^{i\omega x} dx \\ &= -\frac{i}{2} \int_{-\pi}^{\pi} \frac{d}{dx} \left(\frac{e^{i\omega x} - 1}{i\omega} \right) \left(\sum_{n=1}^{\infty} n g_n g_{-n} \sin nx \right) dx .\end{aligned}$$

Integrating by parts, we find

$$\lambda D(\lambda) = -\frac{1}{2\omega} \int_{-\pi}^{\pi} (e^{i\omega x} - 1) \left(\sum_{n=1}^{\infty} n^2 g_n g_{-n} \cos nx \right) dx .$$

Because of (5.20), the integrand is a continuous function of x which is bounded independently of ω . This proves (5.21).

Similar arguments can be applied in order to extend the estimates (5.1) and (5.2) to the case where infinitely many of the g_n are different from zero. However, we shall not go into the details, which are rather tedious.

6. Some relations between the characteristic values.

We shall prove the following results:

Theorem 3. Let the roots of $\Delta(\lambda) + 2$ and of $\Delta(\lambda) - 2$ be denoted as in Section 2. Then

$$(6.1) \quad \sum_{n=1}^{\infty} \left[\lambda'_{2n-1} + \lambda'_{2n} - 2(2n-1)^2 \right] = 0$$

$$(6.2) \quad \lambda'_0 + \sum_{n=1}^{\infty} \left[\lambda'_{2n-1} + \lambda'_{2n} - 2(2n)^2 \right] = 0.$$

Whereas Theorem 1 shows that for large n , λ'_{2n-1} and λ'_{2n} exceed $(2n-1)^2$ and λ_{2n-1} and λ_{2n} exceed $(2n)^2$, it follows from Theorem 3 that the same statement cannot be true for all n .

The next result refers to the case where $g(x)$ is an even function of x , i.e. where

$$g(x) = g(-x) ; \quad g_{-n} = g_n \quad (n = 1, 2, 3, \dots).$$

In this case, the periodic solutions of (2.1) belonging to the characteristic values λ'_{2n-1} and λ'_{2n} are either even or odd periodic functions of x with period 2π . Let

$$\gamma'_1 < \gamma'_2 < \dots < \gamma'_n < \dots$$

be the ordered sequence of those numbers of the set $\lambda'_{2n-1}, \lambda'_{2n}$ to which there belongs an even periodic function of period 2π , and

$$\sigma'_1 < \sigma'_2 < \dots < \sigma'_n < \dots$$

be the ordered sequence of the remaining numbers of the $\lambda'_{2n-1}, \lambda'_{2n}$ to which there belongs an odd periodic solution of (2.1). Similarly, let

$$\gamma_1 < \gamma_2 < \dots < \gamma_n < \dots$$

be the characteristic values belonging to the set of numbers λ_{2n-1} and λ_{2n} to which there belong even solutions of (2.1) which are of period π and

$$\sigma_1 < \sigma_2 < \dots < \sigma_n < \dots$$

the sequence of characteristic values corresponding to odd solutions of period π . Then we have:

Theorem 4:

$$(6.3) \quad \sum_{n=1}^{\infty} (\gamma'_n - \sigma'_n) = -2 \sum_{n=1}^{\infty} g_{2n-1}$$

$$(6.4) \quad \lambda_0 + \sum_{n=1}^{\infty} (\gamma_n - \sigma_n) = -2 \sum_{n=1}^{\infty} g_{2n}.$$

The following comment should be made concerning Theorem 4. For large n ,

$$(6.5) \quad \left\{ \begin{array}{l} |\gamma'_n - \sigma'_n| = \lambda'_{2n} - \lambda'_{2n-1} \\ |\gamma_n - \sigma_n| = \lambda_{2n} - \lambda_{2n-1} \end{array} \right.$$

Therefore, the absolute values of the terms in the sums on the left-hand sides of the equations in Theorem 4 represent the lengths of the intervals of instability, at least for large values of n . On the other hand, A. Erdélyi^[2] has shown that, for sufficiently small values of

$$\sum_{n=1}^{\infty} |g_n|^2 ,$$

the n -th interval of instability is approximately of length $2|g_n|$. Theorem 4 shows that, although Erdélyi's result may not be exact for the individual intervals of instability, there exist a weaker but exact substitute for it in the form of a relation between sums.

We shall now prove Theorem 3, and we shall confine ourselves to a proof of (6.1). We know from Borg's Theorem (Theorem 1) that

$$(6.6) \quad (2n - 1)^2 \left[\lambda'_{2n-1} - (2n - 1)^2 \right]$$

and

$$(6.7) \quad (2n - 1)^2 \left[\lambda'_{2n} - (2n - 1)^2 \right]$$

are bounded for $n \rightarrow \infty$. We also know that $\Delta + 2$ is a function of order of growth $\frac{1}{2}$ and that therefore for a suitable value of the constant c ,

$$(6.8) \quad \Delta + 2 = c \prod_{n=1}^{\infty} \left(1 - \frac{\lambda}{\lambda_{2n-1}} \right) \left(1 - \frac{\lambda}{\lambda_{2n}} \right)$$

unless one of the λ'_n vanishes, in which case we would have to use a slight modification of this formula which will not affect the proof. We know from Theorem 2 that, for large positive values of $\mu = -\lambda$

$$(6.9) \quad \Delta + 2 = 2 \cosh^2 \frac{\pi}{2} \sqrt{\mu} \left[1 - \frac{\pi \sinh \pi \sqrt{\mu}/2}{2 \sqrt{\mu} \cosh \pi \sqrt{\mu}/2} \sum_{n=1}^{\infty} \frac{|g_n|^2}{\mu + n^2} + \mathcal{O}(\mu^{-5/2}) \right].$$

Now consider the behavior of

$$(6.10) \quad L(\mu) = \frac{d}{d\mu} \log \frac{\Delta + 2}{\cosh^2(\pi \sqrt{\mu}/2)}$$

for $\mu \rightarrow \infty$.

From the product representation of $\Delta + 2$ and of $\cosh(\pi \sqrt{\mu}/2)$ we find

$$\begin{aligned} (6.11) \quad L(\mu) &= \sum_{n=1}^{\infty} \left\{ \frac{1}{\mu + \lambda'_{2n-1}} + \frac{1}{\mu + \lambda'_{2n}} - \frac{2}{\mu + (2n-1)^2} \right\} \\ &= - \sum_{n=1}^{\infty} \left\{ \frac{\lambda'_{2n-1} - (2n-1)^2}{(\mu + \lambda'_{2n-1}) [\mu + (2n-1)^2]} + \frac{\lambda'_{2n} - (2n-1)^2}{(\mu + \lambda'_{2n}) [\mu + (2n-1)^2]} \right\} \\ &= - \sum_{n=1}^{\infty} \left[\lambda'_{2n-1} + \lambda'_{2n} - 2(2n-1)^2 \right] \mu^{-2} \\ &\quad + \sum_{n=1}^{\infty} \left[\lambda'_{2n-1} - (2n-1)^2 \right] \frac{\mu [\lambda'_{2n-1} + (2n-1)^2] + \lambda'_{2n-1} (2n-1)^2}{\mu^2 [\mu + (2n-1)^2] [\mu + \lambda'_{2n-1}]} \end{aligned}$$

$$+ \sum_{n=1}^{\infty} \left[\lambda'_{2n} - (2n-1)^2 \right] \frac{\left[\lambda'_{2n} + (2n-1)^2 \right] \mu + \lambda'_{2n} (2n-1)^2}{\mu^2 \left[\mu + (2n-1)^2 \right] \left[\mu + \lambda'_{2n} \right]} .$$

We wish to show that

$$(6.12) \quad L(\mu) = - \sum_{n=1}^{\infty} \left[\lambda'_{2n-1} + \lambda'_{2n} - 2(2n-1)^2 \right] \mu^{-2} + \mathcal{O}(\mu^{-5/2})$$

for $\mu \rightarrow \infty$. For this purpose, we have to estimate the last two sums in (6.11), proving that they are of the order of $\mu^{-5/2}$. Using the boundedness of the expression (6.6) we find that

$$(6.13) \quad \sum_{n=1}^{\infty} \left[\lambda'_{2n-1} - (2n-1)^2 \right] \frac{\mu \left[\lambda'_{2n-1} + (2n-1)^2 \right] + \lambda'_{2n-1} (2n-1)^2}{\left[\mu + (2n-1)^2 \right] \left[\mu + \lambda'_{2n-1} \right]}$$

can be majorized by

$$S = M \sum_{n=1}^{\infty} \frac{\mu + (2n-1)^2}{\left[\mu + (2n-1)^2 \right]^2}$$

where M is a suitable constant. By using a standard procedure we see that S can be written in the form

$$(6.14) \quad 2M \int_0^{\infty} \frac{\mu + t^2}{(\mu + t^2)^2} dt + \mathcal{O}(\mu^{-1}) .$$

Now the integral in (6.14) equals $\pi/2\sqrt{\mu}$ and this proves (6.12).

Next, we shall derive an asymptotic expansion for $L(\mu)$ from (6.9). From some calculations and by using an argument similar to the one we employed in estimating (6.13) we find that

$$(6.15) \quad L(\mu) = \mathcal{O}(\mu^{-5/2})$$

provided that

$$\sum_{n=1}^{\infty} n^2 |\xi_n|^2 < \infty.$$

A comparison of (6.12) and (6.15) proves Theorem 3.

The proof of Theorem 4 may be based on the following remarks:

First, we can show that for large n the pair of numbers γ'_n, σ'_n is identical with the pair $\lambda'_{2n-1}, \lambda'_{2n}$, apart from the ordering of the numbers. To prove this statement, we will have to consider the equation

$$y'' + [\lambda + \epsilon g(x)]y = 0 \quad (0 \leq \epsilon \leq 1)$$

using a similar argument as in the proof of Theorem 1. For $\epsilon = 0$, $\lambda'_{2n-1} = \lambda'_{2n} = (2n-1)^2$. If ϵ increases, the difference $\lambda'_{2n-1} - \lambda'_{2n}$ will, in general, be different from zero, but it will stay small and one of the periodic solutions belonging to these two numbers will be odd, the other, even. Since both λ'_{2n-1} and λ'_{2n} will not leave a certain neighborhood of $(2n-1)^2$ bounded by, say, $(2n-1)^2 - \frac{1}{2}$ and $(2n-1)^2 + \frac{1}{2}$, these two numbers will always be the characteristic values belonging respectively to the n -th even and to the n -th odd periodic solution of period 2π ,

although we do not know whether λ_{2n} belongs to an even or to an odd solution.

From this remark and from Borg's Theorem we see that the series (6.3) and (6.4) converge absolutely and can be majorized by the series $M \sum n^{-2}$ where M is a constant. Furthermore, we know that the numbers

$$\gamma'_n, \sigma'_n, \gamma_n, \sigma_n \quad (\gamma_0 = \lambda_0)$$

are respectively the zeros of

$$y_1(\pi/2, \lambda), y'_2(\pi/2, \lambda), y'_1(\pi/2, \lambda), y_2(\pi/2, \lambda)$$

where y_1, y_2 are the normalized solutions of (2.1) described in Section 2. (For a proof, see Reference [3] or [4]). From the method of solving (2.1) by iteration, we find that, for $\lambda = -\mu$, μ large and positive

$$(6.16) \quad y_1(\pi/2, -\mu) = \cosh(\pi \sqrt{\mu}/2) \left[1 - \sum_{n=1}^{\infty} \frac{g_{2n+1}}{\mu + (2n+1)^2} + \mathcal{O}(\mu^{-3/2}) \right]$$

$$(6.17) \quad y'_2(\pi/2, -\mu) = \cosh(\pi \sqrt{\mu}/2) \left[1 + \sum_{n=1}^{\infty} \frac{g_{2n+1}}{\mu + (2n+1)^2} + \mathcal{O}(\mu^{-3/2}) \right]$$

$$(6.18) \quad y'_1(\pi/2, -\mu) = \sqrt{\mu} \sinh(\pi \sqrt{\mu}/2) \left[1 - \sum_{n=1}^{\infty} \frac{g_{2n}}{\mu + 4n^2} + \mathcal{O}(\mu^{-3/2}) \right]$$

$$(6.19) \quad y_2(\pi/2, -\mu) = \frac{\sinh \pi \sqrt{\mu}/2}{\sqrt{\mu}} \left[1 + \sum_{n=1}^{\infty} \frac{g_{2n}}{\mu + 4n^2} + \mathcal{O}(\mu^{-3/2}) \right]$$

where the $\mathcal{O}(\mu^{-3/2})$ -terms may be differentiated with respect to μ , having a derivative of the order of $\mu^{-5/2}$.

Again, the left-hand sides in (6.16) to (6.19) are functions of μ of order of growth $\frac{1}{2}$, and will admit product representations of the type (6.8), e.g. (for $\lambda_0 \neq 0$, $\gamma_n \neq 0$, $\sigma_n \neq 0$)

$$(6.20) \quad y_1'(\pi/2, -\mu) = c (1 + \mu/\lambda_0) \prod_{n=1}^{\infty} (1 + \mu/\gamma_n)$$

$$(6.21) \quad y_2(\pi/2, -\mu) = c^* \prod_{n=1}^{\infty} (1 + \mu/\sigma_n)$$

where c, c^* are constants. Now we can calculate an asymptotic expansion for

$$\frac{d}{d\mu} \log \frac{y_1'(\pi/2, -\mu)}{y_2(\pi/2, -\mu)}$$

in two different ways, using (6.18) and (6.19) or using (6.20) and (6.21).

By equating these two expansions, we find

$$\frac{1}{\mu} + 2 \sum_{n=1}^{\infty} \frac{g_{2n}}{[\mu + 4n^2]^2} + \mathcal{O}(\mu^{-5/2}) = \frac{1}{\mu + \lambda_0} + \sum_{n=1}^{\infty} \frac{\sigma_n - \gamma_n}{(\mu + \gamma_n)(\mu + \sigma_n)}$$

or

$$2 \sum_{n=1}^{\infty} g_{2n} \mu^{-2} + \mathcal{O}(\mu^{-5/2}) = - \left[\lambda_0 + \sum_{n=1}^{\infty} (\gamma_n - \sigma_n) \right] \mu^{-2} + \mathcal{O}(\mu^{-5/2})$$

which proves (6.4). Equation (6.3) can be proved in the same manner.

Appendix

7. Methods for the computation of Δ

From reference [3], the following results may be taken:

(i) We can define the n-th component Δ_n of

$$(7.1) \quad \Delta = \sum_{n=1}^{\infty} \Delta_n$$

recursively by

$$(7.2) \quad \Delta_n(\lambda) = u_n(\pi, \lambda) + v_n'(\pi, \lambda)$$

where (with the abbreviation $\omega = \sqrt{\lambda}$):

$$(7.3) \quad u_n(x, \lambda) = -\frac{1}{\omega} \int_0^x \sin \omega(x - \xi) g(\xi) u_{n-1}(\xi) d\xi$$

$$(7.4) \quad v_n(x, \lambda) = -\frac{1}{\omega} \int_0^x \sin \omega(x - \xi) g(\xi) v_{n-1}(\xi) d\xi$$

$$u_0 = \cos \omega x, \quad v_0 = \omega^{-1} \sin \omega x, \quad v_n' = dv_n/dx.$$

(ii) An application of the Laplace transformation to (7.2), (7.3) and (7.4) followed by an application of the inversion formula for the Laplace transformation yields the following result: Let

$$(7.5) \quad \Delta_n = \sum_{\ell_1, \ell_2, \dots, \ell_n = -\infty}^{\infty} c(\ell_1, \dots, \ell_n) g_{\ell_1} g_{\ell_2} \dots g_{\ell_n}.$$

Then

$$(7.6) \quad c(\ell_1, \dots, \ell_n) = \frac{1}{2\pi i} \int_{\delta-i\infty}^{\delta+i\infty} k(\ell_1, \dots, \ell_n; p) e^{\pi p d p}$$

where δ is real and positive and where

$$(7.7) \quad k(\ell_1, \dots, \ell_n; p) = (-1)^n \frac{2p - 2i \sum_{v=1}^n \ell_v}{\left[\omega^2 + p^2 \right] \prod_{v=1}^n \left[\omega^2 + (p - 2i\ell_1 - \dots - 2i\ell_v)^2 \right]}$$

A consequence of (7.7) is that

$$(7.8) \quad c(\ell_1, \dots, \ell_n) = A(\omega) \cos \omega \pi + B(\omega) \sin \omega \pi,$$

where $A(\omega)$ and $B(\omega)$ are rational functions of ω the poles of which lie at some or all of the points

$$\omega = 0, \quad \omega = \pm (\ell_r + \ell_{r+1} + \dots + \ell_s)$$

where $1 \leq r \leq s \leq n$. The degree of the denominator of $A(\omega)$ and $B(\omega)$ exceeds the degree of the numerator by at least n .

$A(\omega)$ and $\omega B(\omega)$ are even functions of ω .

(iii) There exists an expression of Δ in terms of an infinite determinant,

$$(7.9) \quad 2 - \Delta = .4 \sin^2 \frac{\pi}{2} \omega \left| \delta_{n,m} + \frac{\varepsilon_{n-m}}{\lambda - 4n^2} \right|$$

where $\delta_{n,m} = 0$ for $n \neq m$ and $\delta_{m,n} = 1$ and where n, m run from $-\infty$ to $+\infty$ in the infinite determinant on the right-hand side of (7.9) with n denoting the rows and m denoting the columns.

We shall now discuss the merits and disadvantages of the three approaches, (i), (ii) and (iii). The first approach, (i.e. (7.2), (7.3) and (7.4)), provides us with the estimate

$$(7.10) \quad |\Delta_n| = \mathcal{O}(\omega^{-n}) \quad \omega \rightarrow +\infty.$$

Also, the same approach permits us to estimate

$$(7.11) \quad e^{-\pi\theta} |\Delta_n|$$

for $\lambda = -\theta^2$, $\theta \rightarrow +\infty$. However, (7.2) and (7.3) are not suitable for computing Δ_n if $n > 2$. The reason for this is that (7.2) and (7.3) produce a large number of terms, many of which disappear or combine with others if we take $x = \pi$.

The second approach (i.e. (7.6), (7.7)) provides us with the statements made above about the nature of $A(\omega)$ and $B(\omega)$ in (7.8) if we evaluate the integral in (7.6) by the method of residues. Still, the number of terms to be considered when evaluating this integral is much larger than the number of final terms since many terms amalgamate. The approach described by (7.6) and (7.7) does not allow us to prove Lemma 2 of Section 4. It does not even make evident the fact that only those of the

$$c(\ell_1, \ell_2, \dots, \ell_n)$$

can be different from zero for which

$$(7.12) \quad \ell_1 + \ell_2 + \dots + \ell_n = 0,$$

although this fact can be derived without any calculations from the remark that the discriminant $\Delta(\lambda)$ must remain unchanged if $g(x)$ is replaced by $g(x - \alpha)$, where α is any real number.

As it happens, the most efficient method of calculating $\Delta(\lambda)$ is still the method originally used by Hill which is based on the expression (7.9) of Δ in terms of an infinite determinant. We shall exemplify this method by applying it to the computation of Δ_2 , Δ_3 and Δ_4 . In doing this, we shall also indicate how to prove Lemma 2 of Section 4.

If we expand the infinite determinant of formula (7.9) in such a manner that we keep terms together which are of the same degree in the g_n , we find that

$$(7.13) \quad \Delta_0 = 2 \cos \omega\pi \qquad \Delta_1 = 0$$

$$(7.14) \quad \Delta_2 = -4 \sin^2 \frac{\pi}{2} \omega \sum_{\ell=1}^{\infty} \sum_{t=-\infty}^{\infty} \frac{\begin{vmatrix} 0 & g_{\ell} \\ g_{-\ell} & 0 \end{vmatrix}}{(\lambda - 4t^2) [\lambda - 4(t + \ell)^2]}$$

$$(7.15) \quad -\Delta_3 \left[4 \sin^2 \frac{\pi}{2} \omega \right]^{-1}$$

$$= \sum_{\ell, m=1}^{\infty} \sum_{t=-\infty}^{\infty} \frac{\begin{vmatrix} 0 & g_{\ell} & g_{\ell+m} \\ g_{-\ell} & 0 & g_m \\ g_{-\ell-m} & g_{-m} & 0 \end{vmatrix}}{(\lambda - 4t^2) [\lambda - 4(t + m)^2] [\lambda - 4(t + \ell + m)^2]}$$

$$(7.16) \quad - \Delta_4 \left[4 \sin^2 \frac{\pi}{2} \omega \right]^{-1}$$

$$= \sum_{\ell, m, k=1}^{\infty} \sum_{t=-\infty}^{\infty} \frac{\begin{vmatrix} 0 & g_{\ell} & g_{\ell+m} & g_{\ell+m+k} \\ g_{-\ell} & 0 & g_m & g_{m+k} \\ g_{-\ell-m} & g_{-m} & 0 & g_k \\ g_{-\ell-m-k} & g_{-m-k} & g_{-k} & 0 \end{vmatrix}}{\left[\lambda - 4t \right]^2 \left[\lambda - 4(t+k) \right]^2 \left[\lambda - 4(t+k+m) \right]^2 \left[\lambda - 4(t+k+m+\ell) \right]^2}.$$

The general law, according to which Δ_n can be expressed as an infinite sum involving n by n determinants, is apparent from (7.15) and (7.16). Now we have to remark briefly about the proof of Lemma 2 (Section 4). We know from (7.8) the general behavior of the coefficient c of a particular product of degree n in the g_{ℓ} . If we make ω purely imaginary and $\lambda = \omega^2$ negative, i.e. if we put

$$\omega = i\theta, \quad \lambda = -\theta^2$$

then, for $\theta \rightarrow \infty$,

$$(7.17) \quad c(\ell_1, \dots, \ell_n) \left[\sin^2 \frac{\pi}{2} \omega \right]^{-1} = \mathcal{O}(\theta^{-d})$$

where d is the smaller of the differences between the degrees of the denominators and the numerators in $A(\omega)$ and $B(\omega)$. (Special attention must be given to the case where these two differences are equal and where d may be greater than either of these two differences because in $A \cos \pi\omega + B \sin \pi\omega$, the asymptotic behavior for $\omega = i\theta$, $\theta \rightarrow +\infty$ may be different

from that of $A \cos \pi \omega$ and of $A \sin \pi \omega$. This case has to be settled by putting $\omega = (1 + i)\theta$, and letting $\theta \rightarrow +\infty$). If we wish to compute d by using (7.17), we may apply the following.

Lemma 3: For $\theta \rightarrow +\infty$,

$$(7.18) \quad \sum_{m_1, \dots, m_r=1}^{\infty} \sum_{t=-\infty}^{+\infty} \prod_{v=1}^n \left[\theta^2 + (t + m_1 + \dots + m_v)^2 \right]^{-1} \cdot (\theta^2 + t^2)^{-1} \\ = \mathcal{O}(\theta^{r-2n-1}).$$

The proof of (7.18) is based on a comparison of the multiple sum in (7.18) with the multiple integral

$$(7.19) \quad \int_0^{\infty} \dots \int_0^{\infty} d\mu_1 \dots d\mu_r \int_{-\infty}^{\infty} d\tau (\theta^2 + \tau^2)^{-1} \prod_{v=1}^n \left[\theta^2 + (\tau + \mu_1 + \dots + \mu_v)^2 \right]^{-1}.$$

By substituting $\theta\tau$, $\theta\mu_1$, \dots , $\theta\mu_n$ for τ , μ_1 , \dots , μ_n , this integral is seen to be equal to

$$\theta^{r-2n-1} \int_0^{\infty} \dots \int_0^{\infty} d\mu_1 \dots d\mu_r \int_{-\infty}^{\infty} d\tau (1 + \tau^2)^{-1} \prod_{v=1}^n \left[1 + (\tau + \mu_1 + \dots + \mu_v)^2 \right]^{-1}$$

and here the integral is a constant independent of θ . On the other hand, it is easily seen that (7.19) is a majorant of the sum in (7.18).

Using Lemma 3, we can prove Lemma 2 as follows: Looking at the representation of Δ_n as a sum of determinants which are divided by certain products of the type appearing in (7.18), and picking a particular product

$$P = g_{\ell_1} \cdots g_{\ell_n}$$

appearing in these determinants, we see that P can appear in infinitely many of these determinants only if several of the subscripts ℓ_1, \dots, ℓ_n are coupled in pairs, say ℓ_1, ℓ_2 and ℓ_3, ℓ_4 etc. such that $\ell_1 = -\ell_2$, $\ell_3 = -\ell_4$ and so on. If we have r such pairs, the coefficient of P in Δ_n is essentially an $(r + 1)$ -fold infinite sum of the type (7.18). But in a determinant of the type appearing in (7.16) (which illustrates the case $n = 4$) at most $[n/2]$ such pairs can appear, and this proves Lemma 2.

The corollary of Theorem 3, as stated in Section 4, is an immediate consequence of the fact that a skew symmetric determinant with an odd number of rows and columns vanishes identically.

Next, we shall describe briefly a method for evaluating the sums involved in Δ_2 , Δ_3 and Δ_4 .

To compute Δ_2 , we need the fact that

$$(7.20) \quad s(\ell) = \sum_{t=-\infty}^{\infty} \left\{ \left[\omega^2 - 4t^2 \right] \left[\omega^2 - 4(t + \ell)^2 \right] \right\}^{-1}$$

$$= \frac{\pi \cos(\pi\omega/2)}{4\omega \sin(\pi\omega/2)} \frac{1}{\omega^2 - \ell^2}$$

for $\ell = \pm 1, \pm 2, \pm 3, \dots$. This relation can be proved by comparing the formulas for Δ_2 , arising from the methods (i) or (ii) described above, with the expression (7.14). But we can also prove (7.20) directly by using the formula

$$\sum_{t=-\infty}^{\infty} \frac{(-1)^t e^{itx}}{\omega^2 - 4t^2} = \frac{\pi \cos(x\omega/2)}{2\omega \sin(\pi\omega/2)},$$

which can be proved by expanding $\cos(x\omega/2)$ in a Fourier series in the interval $-\pi < x < \pi$. Now we have

$$\begin{aligned} \sum_{t=-\infty}^{+\infty} \frac{(-1)^t e^{itx}}{\omega^2 - 4t^2} &= \sum_{t=-\infty}^{+\infty} \frac{(-1)^{t+\ell} e^{-i(t+\ell)x}}{\omega^2 - 4(t+\ell)^2} = (-1)^\ell e^{-i\ell x} \sum_{t=-\infty}^{+\infty} \frac{(-1)^t e^{-itx}}{\omega^2 - 4(t+\ell)^2} \\ &= \frac{\pi \cos(x\omega/2)}{2\omega \sin(\pi\omega/2)} \end{aligned}$$

and therefore

$$\begin{aligned} \sum_{t=-\infty}^{\infty} \frac{1}{[\lambda - 4t^2][\lambda - 4(t+\ell)^2]} &= \frac{1}{2\pi} \int_{-\pi}^{\pi} \sum_{t=-\infty}^{\infty} \frac{(-1)^t e^{itx}}{\omega^2 - 4t^2} \sum_{t=-\infty}^{\infty} \frac{(-1)^t e^{-itx}}{\omega^2 - 4(t+\ell)^2} dx \\ &= \frac{\pi^2 (-1)^\ell}{8\pi\omega^2 \sin^2(\pi\omega/2)} \int_{-\pi}^{\pi} \cos^2 x\omega/2 e^{-i\ell x} dx = \frac{\pi \cos(\omega\pi/2)}{4\omega \sin(\omega\pi/2) [\omega^2 - \ell^2]} \end{aligned}$$

which proves (7.20).

In order to calculate Δ_3 , we have to evaluate the sum

$$(7.21) \quad S(m, \ell) = \sum_{t=-\infty}^{\infty} \left\{ \left[\lambda - 4t^2 \right] \left[\lambda - 4(t+m)^2 \right] \left[\lambda - 4(t+m+\ell)^2 \right] \right\}^{-1}.$$

Using the sums $S(\ell)$ as defined and evaluated in (7.20), we have that $S(\ell)$ can also be written as

$$S(\ell) = \sum_{t=-\infty}^{+\infty} \left\{ \left[\lambda - 4(t+m) \right] \left[\lambda - 4(t+m+\ell) \right] \right\}^{-1}$$

and therefore

$$S(m, \ell) = AS(m) + BS(\ell + m) + CS(\ell)$$

where

$$A = -\frac{1}{4\ell(m+\ell)}, \quad B = \frac{1}{4\ell m}, \quad C = -\frac{1}{4m(m+\ell)}$$

or

$$(7.22) \quad S(m, \ell) = \frac{\pi \cos \pi \omega / 2}{16 \omega \sin \pi \omega / 2} \frac{3\lambda - \ell^2 - m^2 - \ell m}{(\lambda - \ell^2)(\lambda - m^2) \left[\lambda - (\ell + m)^2 \right]}.$$

Obviously, (7.22) and (7.15) will give us the expression for $\Delta_3(\lambda)$ as stated in Theorem 2.

Finally, we have to evaluate formula (7.16) which gives us Δ_4 . For this purpose, we must first write out the 4 by 4 determinants in the numerator; then we must collect all terms which involve the same product of the

g_n , and, finally, we must carry out whatever summations remain. This is a rather tedious job, and we shall not discuss it in detail. All we shall do here is to indicate which sums must be evaluated and how this evaluating can be done

Consider first

$$S(k, m, \ell) = \sum_{t=-\infty}^{\infty} \left\{ \left[\lambda - 4t^2 \right] \left[\lambda - 4(t+k)^2 \right] \left[\lambda - 4(t+k+m)^2 \right] \left[\lambda - 4(t+k+m+\ell)^2 \right] \right\}^{-1}.$$

Using the method applied for the calculation of $S(m, \ell)$ in (7.22), we find that

$$(7.23) \quad S(k, m, \ell) = -\frac{1}{4k(k+m)} S(m, \ell) + \frac{1}{4km} S(k+m, \ell) - \frac{1}{4m(k+m)} S(k, \ell+m).$$

Since

$$\frac{1}{km} = \frac{1}{k(k+m)} + \frac{1}{m(k+m)},$$

we see that $S(k, m, \ell)$ tends toward zero like $\lambda^{-1} S(m, \ell)$ as $\lambda \rightarrow \infty$.

The main difficulty consists in computing the coefficients of $(g_{\ell} g_{-\ell})^2$ and of $g_m g_{-m} g_{\ell} g_{-\ell}$ in Δ_4 . We shall use the following notations:

$$\tilde{S}(\ell) = \sum_{t=-\infty}^{\infty} \left\{ \left[\lambda - 4t^2 \right] \left[\lambda - 4(t+\ell)^2 \right] \right\}^{-2}$$

$$S^*(\ell) = \sum_{t=-\infty}^{\infty} \left[\lambda - 4t^2 \right]^{-2} \left\{ \left[\lambda - 4(t-\ell)^2 \right] \left[\lambda - 4(t+\ell)^2 \right] \right\}^{-1}$$

$$\tilde{S}(\ell, m) = \sum_{t=-\infty}^{\infty} \left[\lambda - 4t^2 \right]^{-2} \left[\lambda - 4(t+\ell)^2 \right]^{-1} \left[\lambda - 4(t+m)^2 \right]^{-1}$$

$$S^*(\ell, m) = \sum_{t=-\infty}^{+\infty} \left\{ \left[\lambda - 4t^2 \right] \left[\lambda - 4(t+\ell)^2 \right] \left[\lambda - 4(t+m)^2 \right] \left[\lambda - 4(t+\ell+m)^2 \right] \right\}^{-1}.$$

Then the coefficient of $(g_\ell g_{-\ell})^2$ on the right-hand side of (7.16), for a fixed ℓ , is

$$(7.24) \quad \frac{1}{2} [S(\ell)]^2 - \frac{1}{2} \tilde{S}(\ell) = -S_\ell^*.$$

The coefficient of $g_\ell g_{-\ell} g_m g_{-m}$, for fixed values of ℓ, m and $\ell > m$ is

$$(7.25) \quad [S(\ell)]^2 - 2\tilde{S}(\ell, m) - S(-\ell, m) - S(\ell, -m) + 2S^*(\ell, m).$$

We observe now that it follows from the formulas after (7.20) that

$$(7.26) \quad \frac{\partial}{\partial \lambda} \sum_{t=-\infty}^{\infty} \frac{(-1)^t e^{itx}}{\lambda - 4t^2} = - \sum_{t=-\infty}^{\infty} \frac{(-1)^t e^{itx}}{(\lambda - 4t^2)^2} = \frac{\partial}{\partial \lambda} \frac{\pi \cos(x\sqrt{\lambda}/2)}{2\sqrt{\lambda} \sin(\pi\sqrt{\lambda}/2)}.$$

By applying the same method to (7.26) which we used in proving (7.20), we find that

$$\begin{aligned} \sum_{t=-\infty}^{\infty} \left\{ \left[\lambda - 4t^2 \right] \left[\lambda - 4(t-\ell)^2 \right] \right\}^{-1} &= \tilde{S}(\ell) \\ &= \frac{(-1)^\ell}{2\pi} \frac{\pi^2}{64\lambda^2 \sin^2(\pi\sqrt{\lambda}/2)} \int_{-\pi}^{\pi} e^{i\ell x} \left[\frac{2\cos(x\sqrt{\lambda}/2)}{\sqrt{\lambda}} + x \sin(x\sqrt{\lambda}/2) \right] \end{aligned}$$

$$\begin{aligned}
 & + \left[\frac{\cos(x\sqrt{\lambda}/2) \cos(\pi\sqrt{\lambda}/2)}{\sin(\pi\sqrt{\lambda}/2)} \right]^2 dx \\
 & = \frac{\pi}{128\lambda^2 \sin^2(\pi\sqrt{\lambda}/2)} \left\{ \frac{\sin\pi\sqrt{\lambda}}{\sqrt{\lambda}} \frac{10\lambda^2 - 2\lambda\ell^2}{(\lambda - \ell^2)^3} + 2\pi \frac{\lambda^2 + \lambda\ell^2}{\ell^2(\lambda - \ell^2)^2} \right\} .
 \end{aligned}$$

By the same type of argument, we find that

$$\begin{aligned}
 S'(\ell) &= \sum_{t=-\infty}^{\infty} \left[\lambda - 4t^2 \right]^{-2} \left[\lambda - 4(t - \ell)^2 \right]^{-1} \\
 &= \frac{\pi}{32\lambda^{3/2} \sin^2(\pi\sqrt{\lambda}/2)} \left\{ \sin\pi\sqrt{\lambda} \frac{3\lambda - \ell^2}{(\lambda - \ell^2)^2} + \frac{\pi\sqrt{\lambda}}{\lambda - \ell^2} \right\}
 \end{aligned}$$

and

$$8\ell^2 S^*(\ell) = -S'(\ell) - S'(-\ell) + 2S(\ell, -\ell)$$

where

$$S(\ell, -\ell) = S(\ell, \ell) .$$

Finally, we find that

$$4\ell_m(\ell-m)\tilde{S}(-\ell, -m) = 4\ell_m(\ell-m)\tilde{S}(\ell, m) = \ell S'(\ell) - m S'(\ell-m) - (\ell-m)S(m, m-\ell)$$

and these formulas permit us to compute all of the sums occurring in the evaluation of Δ_4 . It should be noted that, in writing down these formulas, we have frequently used

$$\sum_{t=-\infty}^{\infty} = \sum_{t=\infty}^{-\infty} = \sum_{\tau=-\infty}^{\infty}$$

where $\tau = -t$.

This concludes the proof of Theorem 2.

References

- [1] G. Borg - Eine Umkehrung der Sturm - Liouvilleschen Eigenwertaufgabe. Acta Mathematica; 78, 1-96 (1946).

- [2] A. Erdélyi - Ueber die rechnerische Ermittlung von Schwingungsvorgaengen etc. Archiv der Elektrotechnik; 29, 473-489 (1935).

- [3] W. Magnus and
A. Shenitzer - Hill's Equation, Part I. General Theory;
N.Y.U., Inst. Math. Sci., Div. EM Res., Research
Report No. BR-22.

- [4] F.W. Schaeferke - See J. Meixner and F.W. Schaeferke, Mathicusche und
Sphaeroidfunktionen, Chapter 1. Springer., Berlin-
Goettingen-Heidelberg (1954).

Distribution List for Research Reports

Contract No. AF 49(638)229

(ONE copy unless otherwise noted)

(3) Commander European Office, ARDC 47 Rue Carstensteen Brussels, Belgium	Commander Air Force Missile Test Center ATTN: Technical Library Patrick Air Force Base, Florida	Department of Mathematics Washington University St. Louis 5, Missouri
Applied Mathematics and Statistics Lab. Stanford University Stanford, California	Department of Mathematics Northwestern University Evanston, Illinois	Department of Mathematics University of Missouri Columbia, Missouri
Department of Mathematics University of California Berkeley, California	Institute for Air Weapons Research Museum of Science and Industry University of Chicago Chicago 37, Illinois	Linda Hall Library ATTN: Mr. Thomas Gillis Document Division 5109 Cherry Street Kansas City 10, Missouri
Commander Air Force Flight Test Center ATTN: Technical Library Edwards Air Force Base, California	Department of Mathematics University of Chicago Chicago 37, Illinois	Commander Strategic Air Command ATTN: Operations Analysis Offutt Air Force Base Omaha, Nebraska
The Rand Corporation Technical Library 1700 Main Street Santa Monica, California	Department of Mathematics University of Illinois Urbana, Illinois	The James Forrestal Res. Center Lib. Princeton University Princeton, New Jersey
Director of Advanced Studies Air Force Office of Scientific Research Post Office Box 2035 Pasadena 2, California	Department of Mathematics Turdue University Lafayette, Indiana	Library Institute for Advanced Study Princeton, New Jersey
Commander Western Development Division ATTN: WDSIT P.O. Box 262 Inglewood, California	Institute for Fluid Dynamics and Applied Mathematics University of Maryland College Park, Maryland	Department of Mathematics Fine Hall Princeton University Princeton, New Jersey
Department of Mathematics Yale University New Haven, Connecticut	Mathematics and Physics Library The Johns Hopkins University Baltimore, Maryland	Commander AF Missile Development Center ATTN: Technical Library Holloman Air Force Base, New Mexico
Chief of Naval Operations Department of the Navy ATTN: OP03EG; Mr. Arthur Kaufman Washington 25, D.C.	Commander HQ Air Research and Development Command Director of Research Andrews Air Force Base Washington 25, D.C.	Commander Air Force Special Weapons Center ATTN: Technical Library Kirtland Air Force Base Albuquerque, New Mexico
(2) Office of Naval Research Department of the Navy ATTN: Code 432 Washington 25, D.C.	Department of Mathematics Harvard University Cambridge 38, Massachusetts	Prof. J. Wolfowitz Mathematics Department White Hall Cornell University Ithaca, New York
Department of Commerce Office of Technical Services Washington 25, D.C.	Department of Mathematics Massachusetts Institute of Technology Cambridge, Massachusetts	Department of Mathematics Syracuse University Syracuse, New York
Director National Security Agency ATTN: Dr. H.H. Campaigne Washington 25, D.C.	Commander Air Force Cambridge Research Center ATTN: Geophysics Research Library L.C. Hanscom Field Bedford, Massachusetts	New York University Institute of Mathematical Sciences Division of Electromagnetic Research ATTN: Professor M. Kline 25 Waverly Place New York 3, N.Y.
Library National Bureau of Standards Washington 25, D.C.	Commander Air Force Cambridge Research Center ATTN: Electronics Research Library L. G. Hanscom Field Bedford, Massachusetts	Department of Mathematics Columbia University ATTN: Professor E.O. Koopman New York 27, N.Y.
National Applied Mathematics Labs. National Bureau of Standards Washington 25, D.C.	Psychological Labs. ATTN: Dr. George A. Miller Memorial Hall Harvard University Cambridge 38, Mass.	Department of Mathematical Statistics Fayerweather Hall ATTN: Dr. Herbert Robbins Columbia University New York 27, N.Y.
Headquarters, USAF Assistant for Operations Analysis Deputy Chief of Staff, Operations, AFMCA Washington 25, D.C.	Department of Mathematics Wayne University ATTN: Dr. Y.W. Chen Detroit 1, Michigan	Department of Mathematics Columbia University ATTN: Professor E.O. Koopman New York 27, N.Y.
(2) Commander Air Force Office of Scientific Research ATTN: SRUB Washington 25, D.C.	Willow Run Research Center University of Michigan Ypsilanti, Michigan	Commander Rome Air Development Center ATTN: Technical Library Griffiss Air Force Base Rome, New York
(2) Commander Air Force Office of Scientific Research ATTN: SRE Washington 25, D.C.	Department of Mathematics Folwell Hall University of Minnesota Minneapolis, Minnesota	Institute for Aeronautical Sciences ATTN: Librarian 2 East 6th Street New York 21, N.Y.
National Science Foundation ATTN: Dr. Leo Cohen Washington 25, D.C.	Department of Mathematics Institute of Technology Engineering Building University of Minnesota Minneapolis, Minnesota	
Commander Air Force Armament Center ATTN: Technical Library Eglin Air Force Base, Florida		

- Institute of Statistics
North Carolina State College of A & E
Raleigh, North Carolina
- Department of Mathematics
University of North Carolina
Chapel Hill, North Carolina
- (2) Office of Ordnance Research
Box CM
Duke Station
Durham, North Carolina
- Department of Mathematics
Duke University
Duke Station
Durham, North Carolina
- Commander
Air Technical Intelligence Center
ATTN: ATIAS-4
Wright-Patterson Air Force Base, Ohio
- Commander
Wright Air Development Center
ATTN: Technical Library
Wright-Patterson Air Force Base, Ohio
- (2) Commander
Wright Air Development Center
ATTN: ARL Technical Library, WORS
Wright-Patterson Air Force Base, Ohio
- (2) Commandant
USAF Institute of Technology
ATTN: Technical Library, MOLI
Wright-Patterson Air Force Base, Ohio
- Department of Mathematics
Carnegie Institute of Technology
Pittsburgh, Pennsylvania
- Department of Mathematics
University of Pennsylvania
Philadelphia, Pennsylvania
- Commander
Arnold Engineering Development Center
ATTN: Technical Library
Tullahoma, Tennessee
- Defense Research Laboratory
University of Texas
Austin, Texas
- Department of Mathematics
Rice Institute
Houston, Texas
- Commander
AF Personnel & Training Research Center
ATTN: Technical Library
Lackland Air Force Base
San Antonio, Texas
- (10) Armed Services Technical Information Agency
Arlington Hall Station
Arlington 12, Virginia
- Department of Mathematics
University of Wisconsin
Madison, Wisconsin
- Mathematics Research Center
ATTN: R.E. Langer
University of Wisconsin
Madison, Wisconsin
- Naval Electronics Laboratory
San Diego 52, California
- Research Laboratory of Electronics
Massachusetts Institute of Technology
Rm. 20B-221
Cambridge 39, Massachusetts
- Signal Corps Engineering Labs.
Technical Documents Center
Evans Signal Laboratory
Belmar, New Jersey
- Commanding General
Signal Corps Engineering Labs.
ATTN: Technical Reports Library
Fort Monmouth, New Jersey
- Chief of Staff
HQ United States Air Force
Pentagon, Washington 25, D.C.
ATTN: AFMRD - 5
- Office of Chief Signal Officer
Signal Plans and Operations Division
Com. Liaison Br., Radio Prop. Section
The Pentagon, Washington 25, D.C.
ATTN: SIGOL - 2, Rm. 20
- Library
Boulder Laboratory
National Bureau of Standards
Boulder, Colorado
- Naval Research Laboratory
Washington 25, D.C.
ATTN: Technical Data Section
- Air Force Development Field Rep.
Naval Research Laboratory
Code 1110
Washington 25, D.C.
- Ballistics Research Laboratory
Aberdeen Proving Ground
Aberdeen, Maryland
ATTN: Dr. Leats Pullen
- Massachusetts Institute of Technology
Lincoln Laboratory
P.O. Box 390
Cambridge 39, Massachusetts
ATTN: Dr. T.J. Carroll
- Mr. Keeve Siegel
Willow Run Research Center
Willow Run Airport
Ypsilanti, Michigan
- Willow Run Research Center
University of Michigan
Willow Run Airport
Ypsilanti, Michigan
ATTN: Dr. C.L. Dolph
- Director
Naval Research Laboratory
Code 3440
Washington 25, D.C.
ATTN: Dr. L.C. van Atta
- Director
Naval Research Laboratory
Washington 25, D.C.
ATTN: Mr. Robert E. Roberson
- National Bureau of Standards
Computation Laboratories
Washington 25, D.C.
ATTN: Dr. John Todd
- Dr. A.G. McNish
National Bureau of Standards
Washington 25, D.C.
- Dr. Derrick H. Lehmer
Department of Mathematics
University of California
Berkeley, California
- Division of Electrical Engineering
Electronics Research Laboratory
University of California
Berkeley 4, California
ATTN: Dr. Samuel Silver
- Dr. Joseph Kaplan
Department of Physics
University of California
Los Angeles, California
- Dr. A. Erdelyi
California Institute of Technology
1201 E. California Street
Pasadena, California
- Dr. Robert Kalaba
Electronics Division
Rand Corporation
Santa Monica, California
- Stanford Research Institute
Stanford, California
ATTN: Dr. J.V.N. Granger
Head, Radio Systems Laboratory
- Dr. Vic Twersky
Electronics Defense Laboratory
Box 205
Mountain View, California
- Hughes Aircraft Company
Research and Development Library
Culver City, California
ATTN: M. Bodner
- Georgia Institute of Technology
Engineering Experimental Station
Atlanta, Georgia
ATTN: Dr. James E. Boyd
- Applied Physics Laboratory
The Johns Hopkins University
8621 Johns Hopkins Avenue
Silver Spring, Maryland
ATTN: Mr. F.T. McClure
- Dr. Donald E. Kerr
Department of Physics
The Johns Hopkins University
Baltimore 18, Maryland
- Dr. A. Weinstein
Institute of Fluid Dynamics and
Applied Mathematics
University of Maryland
College Park, Maryland
- Professor J. A. Pierce
Harvard University
Cambridge 38, Massachusetts
- Dr. F.M. Wiener
Bob Beranek and Newman Inc.
16 Elliot Street
Cambridge 38, Massachusetts
- Mrs. Marjorie L. Cox, Librarian
Technical Reports Collection
Room 303A, Pierce Hall
Harvard University
Cambridge 38, Massachusetts
- Dr. Arthur A. Oliner
Microwave Research Institute
Polytechnic Institute of Brooklyn
55 Johnson Street
Brooklyn, N.Y.
- Professor J.H. Mulligan
School of Engineering
New York University
New York, N.Y.
- Dr. H.G. Booker
School of Electrical Engineering
Cornell University
Ithaca, N.Y.
- Professor Bernard Epstein
Department of Mathematics
Stanford University
Stanford, California
- Professor Albert Heins
Carnegie Institute of Technology
Pittsburgh, Pennsylvania

Professor Fred A. Ficken
University of Tennessee
Knoxville, Tennessee

Miss Barbara C. Grimes, Librarian
Federal Communications Commission
Washington 25, D.C.

Carnegie Institute of Washington
Department of Terrestrial Magnetism
5241 Broad Branch Road, N.W.
Washington 15, D.C.
ATTN: Library

Mathematical Reviews
190 Hope Street
Providence, Rhode Island

Mr. Martin Katzin
154 Fleetwood Terrace
Silver Spring, Maryland

Prof. R.H. Bissinger
Lebanon Valley College
Annville, Pennsylvania

Applied Physics Laboratory
The Johns Hopkins University
3621 Georgia Avenue
Silver Spring, Maryland
ATTN: Dr. B.S. Goumry

Dr. Charles H. Papas
Dept. of Electrical Engineering
California Institute of Technology
Pasadena, California

Dr. Rodman Doll
311 W. Cross St.
Ypsilanti, Michigan

California Institute of Technology
Pasadena 4, California
ATTN: Mr. Calvin Wilcox

Technical Director
Combat Development Dept.
Army Electronic Proving Ground
Fort Huachuca, Arizona

National Bureau of Standards
Boulder, Colorado
ATTN: Dr. W.R. Gallet

Mrs. A.M. Gray
Engineering Library, Plant 5
Grumman Aircraft Corp.
Bethpage, L.I., N.Y.

Professor Bernard Friedman
Dept. of Mathematics
University of California
Berkeley, California

Dr. Jane Scanlon
224-03 67th Avenue
Bayside 64, N.Y.

Dr. Solomon L. Schwebel
3689 Louis Road
Palo Alto, California

Engineering Library
University of California
405 Hilgard Avenue
Los Angeles 24, California

University of Minnesota
The University Library
Minneapolis 14, Minnesota
ATTN: Exchange Division

Lincoln Laboratory
Massachusetts Institute of Technology
P.O. Box 73
Lexington 73, Massachusetts
ATTN: Dr. Shou Chin Wang, Rm. C-351

Technical Research Group
17 Union Square West
New York 3, N.Y.
ATTN: Dr. L. Goldmuntz

Hoffman Laboratories Inc.
Advanced Development Section
3761 South Hill Street
Los Angeles 7, California
ATTN: Dr. Richard B. Barrar

Institute of Fluid Dynamics and
Applied Mathematics
University of Maryland
College Park, Maryland
ATTN: Dr. Elliott Montroll

Brandeis University
Waltham, Massachusetts
ATTN: Library

General Electric Company
Microwave Laboratory
Electronics Division
Stanford Industrial Park
Palo Alto, California
ATTN: Library

Dr. John B. Smyth
Smyth Research Associates
3930 4th Avenue
San Diego 3, California

Dr. Georges G. Weill
Electrical Engineering
California Institute of Technology
Pasadena, California

Naval Research Laboratory
Washington 25, D.C.
ATTN: Dr. Henry J. Passerini
Code 5278 A

Dr. George Kear
5 Culver Court
Orinda, California

California Institute of Technology
Electrical Engineering
Pasadena, California
ATTN: Dr. Zohrab A. Kaprielian

Prof. Nathan Marcovitz
Microwave Research Institute
Brooklyn Polytechnic
55 Johnson Street
Brooklyn, N.Y.

Dr. Lester Kraus
4935 Whitehaven Way
San Diego 10, California

Dr. Jerry Shmoyes
Dept. of Electrical Engineering
Brooklyn Polytechnic
85 Livingston Street
Brooklyn, N.Y.

Dr. I. Kolodner
Dept. of Mathematics
University of New Mexico
Albuquerque, New Mexico

Dr. Harry Hochstadt
Dept. of Mathematics
Polytechnic Institute of Brooklyn
Johnson and Jay Streets
Brooklyn, N.Y.

Hyon Eastern Inc.
75 Cambridge Parkway
Cambridge, Massachusetts
ATTN: Seymour Stein

Mr. K.E. Kelleher, Section Head
Melpar, Inc.
3000 Arlington Boulevard
Falls Church, Virginia

Department of Engineering
Brown University
Providence, R.I.
ATTN: Dr. V.M. Papadopoulos

Wayne State University
Kresge-Hocker Science Library
5250 Second Boulevard
Detroit 2, Michigan

Dr. J. Brandstatten
Stanford Research Institute
S. Pasadena, California

ARBA
1 Bond Street
Westbury, L.I., N.Y.
ATTN: Dr. Norman Spector

Varian Associates
611 Hansen Way
Palo Alto, California
ATTN: (Mrs.) Perry Conway
Technical Librarian

Air Force Cambridge Research Center
Laurence G. Hanscom Field
Bedford, Massachusetts
ATTN: Dr. Ming S. Wong, CRRKP

Professor C. A. Wootton, Director
Eaton Electronics Research Laboratory
McGill University
Montreal, Canada

Dr. D.S. Jones
University of North Staffordshire
Keele, Staffordshire
England

Science Abstracts
Institute of Electrical Engineers
Savoy Place
London W.C. 2, England
ATTN: R.M. Crowther

Dr. Jean-Claude Simon
Centre de Recherche techniques
Compagnie generale de T.S.F.
Paris 19, France

Professor A. van Wijngaarden
Mathematisch Centrum
2^e Boerhaavestraat 49
Amsterdam-Zuid, Holland

Dr. C.J. Bouwkamp
Philips Research Laboratories
Eindhoven, Netherlands

Dr. E.T. Copson
Department of Mathematics
United College
University of St. Andrews
St. Andrews, Scotland

Université de Paris
Cabinet du Département
des Sciences Mathématiques
Institut Henri Poincaré
11 Rue Pierre Curie
Paris 5^e, France

Dr. W. Elwyn Williams
Dept. of Applied Math.
University of Liverpool
Liverpool, England

University of Cambridge
Cavendish Laboratory
Cambridge, England
ATTN: Prof. Philip Clemmow

Technische Hogeschool
Instituut voor Toegepaste Wiskunde
Jaffalaan 162
Delft, Holland
ATTN: Prof. R. Timman

Instituto de Física Teórica
Rue Pamplona, 145
S. Paulo, Brasil

Dr. H. Bremmer
Philips Research Laboratories
Eindhoven, Netherlands

Electrotechnical Laboratory
Nagatsubo, Chiyoda-ku
Tokyo, Japan
ATTN: Library

Dr. A.T. De Hoop
Laboratorium voor Electrotechniek
Technische Hogeschool
Kanaalweg 2 B
Delft, Netherlands

JUN 29 1978		
JUL 24 1978		
FEB 2		
DEC 5 1994		
DEC 16 1994		
AUG 1 1978		
MAY 1977		
AUG 1 1978		
SEP 1 1978		
OCT 1 1978		
NOV 1 1978		
DEC 1 1978		
JAN 1 1979		
FEB 1 1979		
MAR 1 1979		
APR 1 1979		
MAY 1 1979		
JUN 1 1979		
JUL 1 1979		
AUG 1 1979		
SEP 1 1979		
OCT 1 1979		
NOV 1 1979		
DEC 1 1979		
JAN 1 1980		
FEB 1 1980		
MAR 1 1980		
APR 1 1980		
MAY 1 1980		
JUN 1 1980		
JUL 1 1980		
AUG 1 1980		
SEP 1 1980		
OCT 1 1980		
NOV 1 1980		
DEC 1 1980		
JAN 1 1981		
FEB 1 1981		
MAR 1 1981		
APR 1 1981		
MAY 1 1981		
JUN 1 1981		
JUL 1 1981		
AUG 1 1981		
SEP 1 1981		
OCT 1 1981		
NOV 1 1981		
DEC 1 1981		
JAN 1 1982		
FEB 1 1982		
MAR 1 1982		
APR 1 1982		
MAY 1 1982		
JUN 1 1982		
JUL 1 1982		
AUG 1 1982		
SEP 1 1982		
OCT 1 1982		
NOV 1 1982		
DEC 1 1982		
JAN 1 1983		
FEB 1 1983		
MAR 1 1983		
APR 1 1983		
MAY 1 1983		
JUN 1 1983		
JUL 1 1983		
AUG 1 1983		
SEP 1 1983		
OCT 1 1983		
NOV 1 1983		
DEC 1 1983		
JAN 1 1984		
FEB 1 1984		
MAR 1 1984		
APR 1 1984		
MAY 1 1984		
JUN 1 1984		
JUL 1 1984		
AUG 1 1984		
SEP 1 1984		
OCT 1 1984		
NOV 1 1984		
DEC 1 1984		
JAN 1 1985		
FEB 1 1985		
MAR 1 1985		
APR 1 1985		
MAY 1 1985		
JUN 1 1985		
JUL 1 1985		
AUG 1 1985		
SEP 1 1985		
OCT 1 1985		
NOV 1 1985		
DEC 1 1985		
JAN 1 1986		
FEB 1 1986		
MAR 1 1986		
APR 1 1986		
MAY 1 1986		
JUN 1 1986		
JUL 1 1986		
AUG 1 1986		
SEP 1 1986		
OCT 1 1986		
NOV 1 1986		
DEC 1 1986		
JAN 1 1987		
FEB 1 1987		
MAR 1 1987		
APR 1 1987		
MAY 1 1987		
JUN 1 1987		
JUL 1 1987		
AUG 1 1987		
SEP 1 1987		
OCT 1 1987		
NOV 1 1987		
DEC 1 1987		
JAN 1 1988		
FEB 1 1988		
MAR 1 1988		
APR 1 1988		
MAY 1 1988		
JUN 1 1988		
JUL 1 1988		
AUG 1 1988		
SEP 1 1988		
OCT 1 1988		
NOV 1 1988		
DEC 1 1988		
JAN 1 1989		
FEB 1 1989		
MAR 1 1989		
APR 1 1989		
MAY 1 1989		
JUN 1 1989		
JUL 1 1989		
AUG 1 1989		
SEP 1 1989		
OCT 1 1989		
NOV 1 1989		
DEC 1 1989		
JAN 1 1990		
FEB 1 1990		
MAR 1 1990		
APR 1 1990		
MAY 1 1990		
JUN 1 1990		
JUL 1 1990		

PRINTED IN U. S. A.

MIT
BR-
28 Magnus.

c. 1
Discriminant of Hill's
equation.

MIT
BR-
28 Magnus.

c. 1
Discriminant of Hill's
equation.

N. Y. U. Institute of
Mathematical Sciences
25 Waverly Place
New York 3, N. Y.

